

SYNERGY® V

Contec's Synergy® V, model RT-U63CD supports the latest advanced-digital / DVR set-top terminals from the industry's leading manufacturers. It also has many innovative features designed to simplify its programming / operation and is OCAP compliant.

- **Supports 5-Devices**
 - Motorola DCT 64xx DVR, other cable set-top terminals
 - TV
 - VCR
 - DVD
 - AUDIO – A/V receivers, amplifiers, CD
- **OCAP Compliant**
- **Point and Press® Programming**
 - Programs TV, VCR, DVD, AUDIO devices without setup codes
- **Continuous Code Entry Programming**
 - Enter multiple set-up codes while in programming mode, allowing faster set-up of devices
- **Illuminated Mode Buttons**
 - Indicates device being operated
- **Memory Guard®**
 - Eliminates reprogramming after battery changes
- **Mode Lock™**
 - Locks remote to cable mode, eliminating unintentional mode changes
- **All Power SmartKey®**
 - User-programmable to transmit multiple functions, simplifying operation and reducing key presses
- **Channel Memory Buttons**
 - Store favorite or revenue-generating channels
 - “Seamless” VOD access
- **Reset, Time-out features**
- **Programmable Input Button**



Model RT-U63CD-S

SYNERGY[®] V

Universal Digital / DVR Remote Control

Illuminate / select electronic device being operated. Press Mode, then...
 CBL - for Cable mode
 TV - for TV mode
 VCR - for VCR mode
 DVD - for DVD mode
 AUDIO - for Audio mode

Access Program Guide

Access on-screen display for cable device

Moves through on-screen display or cable guide menu (▲, ▼, ►, ◀)

Functions set by cable operator (A, B, C, D)

Day◀ / ► in cable guide

Replay previous few seconds of program (DVR set-top terminals only)

Listing of recorded programs (DVR set-top terminals only)

Rewind DVR, VCR, DVD

Stop DVR, VCR, DVD

Change viewing aspect of cable device

PIP on / off

Swap PIP & and main screen

Selects video source

Channel memory buttons (may be labeled or pre-set by cable operator)



CBL & TV on / off (programmable)

Individual device on / off

Access on-screen Help for Cable set-top terminal

Display channel / program information

Move +/- through on-screen displays, Program Guide

Selects highlighted on-screen or cable guide choice

Exit any on-screen display

Access Video-On-Demand

Recall pre-selected favorite channels

Return to last selected channel

Display live TV programming (DVR set-top terminals only)

Fast-forward DVR, VCR, DVD

Play DVR, VCR, DVD

Record DVR, VCR

Pause DVR, VCR, DVD

Digital Music

Move PIP screen

PIP channel +/-

Access Pay-Per-View

Specifications

- Dimensions - 2.5" x 9.0" x 1.1"
- Weight - 5.0 ounces (w/out batteries)
- Operating Range - Exceeds 30 feet
- Horizontal deviation - 30° min., 45° typical
- Vertical deviation - 25° min., 45° typical
- Battery Requirements - 2 "AA" size batteries
- Packaging - 100 units / box

Quality & Field Performance

- Contec's remotes controls are manufactured to meet and exceed OEM standards for quality, reliability and performance
- Contec remote controls are manufactured in ISO 9002 certified facilities

Warranty

- All Contec remotes are covered by a 5-year warranty against electronic / performance-related failure
- All Contec remotes are covered by a 1-year warranty on silk-screened printing

Pricing / Ordering Information

- To order these remotes, specify model...
 - RT-U63CD (black)
 - RT-U63CD-S (silver)
 - Price includes 2 "AA" batteries
 - Custom logos available
- For more information on this or other Contec remote controls, or the name of the Contec representative nearest you, please contact us at the numbers shown below

Contec Holdings, Ltd.
 1011 State Street
 Schenectady, NY 12307-1511
 Phone: 1-800-382-2723
 Fax: 1-518-382-8452
 www.gocontec.com

Contec Holdings, Ltd.

RT-U62CD-S 08/06